# **USER'S GUIDE**

YP12583(SECONDS CARTOON, MULTI FUNCTION SPORT LCD WATCH)

Quartz Movement EL Backlight

Stopwatch

Countdown Timer

Chime

5 Alarms

Dual Time

Pacer

100 Years Calendar

Battery(CR2025

100M Water Resistant


+SR626SW)

# **ATTENTION**

- 1. Never try to open the case or remove its back cover.
- 2.Do not operate buttons underwater.
- 3. Should moisture appear inside the watch, have it checked immediately by your dealer. Otherwise it can cause erosion of the metal parts of the watch.
- 4. Though the watch is designed to withstand normal use, you should avoid rough use or dropping the watch.
- 5. Avoid exposing the watch to temperature extremes.
- 6.Wipe the watch with dry ,soft cloth only. Avoid allowing it to come into direct contact with chemical materials, which can cause deterioration of the plastic parts of the watch.
- Avoid to wear the watch in electromagnetic, static conditions.

### **BUTTONS**


• Button operation are indicated using the letters shown in the illustration.



- A -- Reset
- B -- Mode
- C -- EL Backlight
- D -- Start/Stop

### DISPLAY

• The screen shown in below:



#### **ADJUST HANDS**

- Pull out the crown, turn to adjust the hour and minutes hands;
- Push the crown go back the normal position after the time set;



#### MODE SELECTION

 Press "B" to change mode to mode in the following Sequence:
Timekeeping Mode - Stopwatch Mode -Countdown Mode - Alarm Mode -Dual Time Mode - Pacer Mode.

### a TIMEKEEPING

- 12/24H Format;
- Hour, Minutes, Seconds, Month, Date, Day of week;
- · 100 years Calendar(2000~2099).

# **b** STOPWATCH

- 1/100 second unit;
- Measuring range: 0'00"00 ~ 23:59'59".



**%**¦⊚ ₹

#### C COUNTDOWN

Countdown range:
23:59'59" ~ 0'00"00.



# d ALARM

- 5 Alarms;
- · Hourly time signal;
- The alarm sounds at the preset time each day.

# e DUAL TIME

 The time for other time zone.



# f PACER

10 tempo.



### (a) TIMEKEEPING

#### 12/24H Format

 In the timekeeping mode, press "D" to switch between 12/24 formats.



#### Time Setting

 In the timekeeping mode press and hold"A" until the seconds to flash; (flashing indicated in set mode)



2. Press "D" to reset the seconds;



3. Press "B" to change the next selection;



4. Press "D" to increase the number, press and hold to increase at high speed;



- Repeat step 3 and 4,the selection in the following sequence:
  Seconds - Hour - Minutes - Year - Month -Date;
- Press "A" to exit the set state, after you set (The day of week is auto displayed in accordance with year, month and date setting).

### **BACKLIGHT**

 The backlight that uses an EL(electro-luminescent) cause the display to glow for easy reading in the dark.

#### Use EL Backlight


 In the timekeeping mode press "C" to illuminate the display about 3 seconds.




# **b** STOPWATCH

#### A Lap Time

stopwatch;





2. To stop the stopwatch by pressing "D" again;



3. Press "A" to reset the stopwatch.



#### Split Time



1. In the stopwatch mode press "D" to start the stopwatch;



2. Press "A" to display the split time, stopwatch timing continues internally;



3. Press "A" to clear the split time and to continue time measurement:



- 4. Repeat step 2 and 3, you can measure the multi split time;
- 5. Press "D" to stop the stopwatch.

### COUNTDOWN

 When the countdown reaches zero, the alarm sounds for about 60 seconds and press any button to break it.

#### **Countdown Timer Setting**

1. In the countdown mode, press "A" the hour to flash; (flashing indicated in set mode)



2. Press "D" to increase the hour ,press and hold to increase at high speed;



3. Press "B" to select the minutes:



4. Press "D" to increase the minutes, press and hold to increase at high speed;



- 5. Repeat step 3 and 4, the selection in the following sequence: Hour - Minutes - Seconds:
- 6. Press "A" to exit the set state, after you set.

#### Use Countdown Timer

1.Press "D" to start the countdown;



2. To pause the countdown by pressing "D" again.

### d ALARM

• The alarm sounds at the preset time each day for about 60 seconds, press any button to break it.

#### **Alarm and Chime**

 In the alarm mode, press "C" to select chime, Alarm1 ~ Alarm5.



· In the chime state, press "D" to on/off the chime .



• In the Alarm1 ~ Alarm5 state, press "D" to on/off the alarm.



#### Alarm1 Setting

1. In the alarm mode, press "A" the hour to flash(flashing indicated in set mode);



2. Press "D" to increase the hour, press and hold to increase at high speed;



3. Press "B" to select the minutes;



4. Press "D" to increase the minutes, press and hold to increase at high speed;



- 5. Press "A" to exit the set state, after you set.
- · Setting and operation of the Alarm1~Alarm5 are the same.

### **e** DUALTIME

#### **Dual Time Setting**

1. In the dual time mode. press "A" the hour to flash: (flashing indicated in set mode)



2. Press "D" to increase the hour, press and hold to increase at high speed;



3. Press "B" to select the minutes:



4. Press "D" to change the minutes; (press once change 30 minutes)



5. Press "A" to exit the set state, after you set.

# PACER

#### Use The Pacer

1. In the pacer mode, the tempo number flash:



2. Press "A" select the tempo in the following sequence: 10 - 20 - 30 - 40 - 60 - 80 - 120 - 160 -240 - 320:



3. Press "D" to start:



4. To stop it press "D" again.

