# **USER'S GUIDE**

YP11532(SECONDS CARTOON, MULTI FUNCTION SPORT WATCH



EL Backlight



Stopwatch



**Dual Time** 



Countdown Timer



100 Years Calendar



5 Alarms



Pacer



Chime



**BUTTONS** 

D -- Start / Stop

100M Water Resistant



· Button operation are indicated using the

letters shown in the illustration.


Battery(CR2025)

### **ATTENTION**

- 1. Never try to open the case or remove its back cover.
- 2. Do not operate buttons underwater.
- 3. Should moisture appear inside the watch, have it checked immediately by your dealer. Otherwise it can cause erosion of the metal parts of the watch.
- 4. Though the watch is designed to withstand normal use, you should avoid rough use or dropping the watch.
- 5. Avoid exposing the watch to temperature extremes.
- 6. Wipe the watch with dry, soft cloth only. Avoid allowing it to come into direct contact with chemical materials, which can cause deterioration of the plastic parts of the watch.
- 7. Avoid to wear the watch in electromagnetic, static conditions

# **DISPLAY**

· The screen shown in below:



### **BACKLIGHT**

· The backlight that uses an EL (electroluminescent)cause the display to glow for easy reading in the dark.

### Use EL Backlight

· In the timekeeping mode, press "C" to illuminate the display about 3 seconds.



### **MODE SELECTION**

· Press "B" to change mode to mode in the following sequence: Timekeeping Mode - Stopwatch Mode -Countdown Mode → Alarm Mode → Dual Time Mode → Pacer Mode.

### (a) TIMEKEEPING

- · 12/24H Format;
- · Hour, Minutes, Seconds, Day of week, Month, Date;
- 100 years Calendar  $(2000 \sim 2099).$



### (b) STOPWATCH

- · 1/100 second unit;
- · Measuring range: 0'00"00 ~ 23:59'59".



### (C) COUNTDOWN

· Countdown range: 23:59'59" ~ 0'00"00.



### (d) ALARM

- 5 Alarms;
- · Hourly time signal;
- · The alarm sounds at the preset time each day.



### (e) DUALTIME

· The time for other time zone.



# f PACER

· 10 tempo.



# a TIMEKEEPING

#### 12/24H Format

· In the timekeeping mode, press "D" to switch between 12/24H formats.



#### Time Setting

1. In the timekeeping mode, press "A" the seconds to flash(flashing indicated in set mode);



2. Press "D" to reset the seconds:




3. Press "B" change to the next selection;



4. Press "D" to increase the number, press and hold to change at high speed;




- 5. Repeat step 3 and 4, the selection in the following sequence: Seconds - Hour - Minutes - Year - Month -Date:
- 6. Press "A" to exit the set state, after you set (The day of week is auto displayed in accordance with year, month and date setting).



# b STOPWATCH

### A Lap Time





2. To stop the stopwatch by pressing "D" again;



3. Press "A" to reset the stopwatch.



#### Split Time



1. In the stopwatch mode, press "D" to start the stopwatch;



2. Press "A" to display the split time, stopwatch timing continues internally;



3. Press "A" to clear the split time and to continue time measurement;



- 4. Repeat step 2 and 3, you can measure the multi split time;
- 5. Press "D" to stop the stopwatch.

### C COUNTDOWN

 When the countdown reaches zero, the alarm sounds for about 60 seconds and press any button to break it.

### **Countdown Timer Setting**

 In the countdown mode, press "A" the hour to flash(flashing indicated in set mode);



2. Press "D" to increase the hour, press and hold to increase at high speed;



3. Press "B" change to the next selection;



4. Press "D" to increase the number, press and hold to change at high speed;



- Repeat step 3 and 4, the selection in the following sequence:
   Hour - Minutes - Seconds;
- 6. Press "A" to exit the set state, after you set.

#### **Use Countdown Timer**

1. Press "D" to start the countdown:



To pause the countdown by pressing "D" again.

## d ALARM

 The alarm sounds at the preset time each day for about 60 seconds, press any button to break it.

#### **Alarm and Chime**

In the alarm mode, press
 "C" to select chime,
 Alarm1 ~ Alarm5.



• In the chime state, press "D" to on/off the chime.



• In the Alarm1 ~ Alarm5 state, press "D" to on/off the alarm.



#### **Alarm1 Setting**

In the alarm mode, press
 A " the hour to flash
 (flashing indicated in set mode):



2. Press "D" to increase the hour, press and hold to increase at high speed;



3. Press "B" to select the minutes;




4. Press "D" to increase the minutes, press and hold to increase at high speed;



- 5. Press "A" to exit the set state, after you set.
- Setting and operation of the Alarm1~Alarm5 are the same.

# e DUALTIME

### **Dual Time Setting**





 Press "D" to increase the hour, press and hold to increase at high speed;



3. Press "B" to select the minutes;



4. Press "D" to change the minutes; (press once change 30 minutes)



5. Press "A" to exit the set state, after you set.

# f PACER

#### Use The Pacer

1. In the pacer mode, the tempo number flash;



2. Press "A" select the tempo in the following sequence:
10 - 20 - 30 - 40 - 60 - 80 - 120 - 160 - 240 - 320:



3. Press "D" to start:



4. To stop it press "D" again.

